NEW COMPUTER LAB
SEE PART PLAN DWG E05-1

CP-1
NEW POWER PANEL CP-1 FOR COMPUTER LAB, SPEECH, PSYCH. AND E.S.S.

LIGHTING CIRCUIT CONTINUES ON DWG. NO. E05-4

PULL BOX SIZE AS REQUIRED

NOTE:
1. ALL EXISTING FLUORESCENT LIGHTING FIXTURES SHOWN TO BE RELOCATED SHALL BE INSTALLED WITH NEW ELECTRONIC BALLAST & NEW LAMPS.

NEW 2" SAN. DROP & CONN. TO EXIST. SAN
NEW 1½" VENT RISE & CONN. TO EXIST VENT ABOVE CLG. EXACT LOCATION SHALL BE VERIFIED IN FIELD
NEW HANDWASH LAV. SHALL BE ELKAY MODEL # ELV 2219 W/LK 412 WRIST BLADE HANDLES, 11½" HIGH GOOSE NECK. LK-174 GRID STRAINER. MCGUIRE 8902 TRAP & 167 FLEX. SUPPLY
CONN. NEW ½" H & CW TO EXIST IN CRAWL SPACE BELOW

STOR.

PART PLAN KITCHEN - PLUMBING
SCALE - 1/8" = 1'-0"

EXISTING EXIT SIGNS DESIGNATED TO BE REMOVED AND REINSTALLED TO ALLOW FOR NEW CEILING INSTALLATION

RECONNECT TO EXISTING CIRCUIT. EXTEND CONDUIT AND WIRE AS REQUIRED

EXISTING WIREMOLD AND FEEDER FROM RECEPTACLE CIRCUIT TO BE DISCONNECTED AND REMOVED. EXISTING KNOCK-OUT TO BE CAPPED. CONNECT EMERGENCY LIGHT TO LINE SIDE OF CORRIDOR LIGHTING CIRCUIT, 2 #12 IN #5W WIREMOLD

TO CP1 PANEL CIRCUIT #1

EXISTING CALL SWITCH TO BE REMOVED

EXISTING CABLE TV OUTLET TO BE REMOVED

EXISTING SPEAKER TO BE REMOVED

PSYCH.

E.S.L.

SPEECH

4 #3 AND 1 #8 GND - 1½" C MOUNT ABOVE NEW SUSPENDED CEILING TIGHT TO STRUCTURE SEE RISER DIAGRAM DWG. NO. E05-2

DISCONNECT SWITCH

STORAGE

NEW TRANSFORMER 30 KVA, DRY TYPE, FLOOR MOUNTED 480V PRIMARY 120/208V SECONDARY

3 #8 AND 1 #8 GND - 1" C MOUNT CONDUIT ABOVE SUSPENDED CEILING TIGHT TO STRUCTURE

3 - EXISTING FLUORESCENT FIXTURES TO BE REMOVED

RECONNECT TO EXISTING CIRCUITS. EXTEND CONDUIT AND WIRE AS REQUIRED

EXISTING WIREMOLD AND FEEDER FROM RECEPTACLE CIRCUIT TO BE DISCONNECTED AND REMOVED. EXISTING KNOCK-OUT TO BE CAPPED. CONNECT EMERGENCY LIGHT TO LINE SIDE OF CORRIDOR LIGHTING CIRCUIT, 2 #12 - IN #5W WIREMOLD

MATCH LINE SEE DWG. NO. E05-4

EXISTING FLUORESCENT FIXTURES TO BE REMOVED

RECONNECT NEW LIGHTING FIXTURES TO EXISTING BRANCH CIRCUIT. SEE GENERAL NOTES DWG. NO. E05-1

- EXISTING FLUORESCENT FIXTURES TO BE REMOVED

EXISTING SMOKE DETECTORS DESIGNATED TO BE REMOVED AND REINSTALLED TO ALLOW FOR NEW CORRIDOR CEILING INSTALLATION.

WHEELCHAIR LIFT 3/4 HP, 120V - 1Ø 12.0 FLA

- EXISTING 1'-0" x 2'-0" FLUORESCENT FIXTURES TO BE REMOVED

DISCONNECT AND REMOVE DISHWASHER DIS. SW. STARTER AND CONTROLS. REMOVE ALL CONDUIT AND WIRE BACK TO SOURCE.

REMOVE EXIST. DISHWASHER, GARBAGE DISPOSER & BOOSTER HEATER AND ALL ASSOC. PIPING. CAP BELOW FL. OR IN WALLS AS REQUIRED

EXISTING WIREMOLD AND FEEDER FROM RECEPTACLE CIRCUIT TO BE DISCONNECTED AND REMOVED. EXISTING KNOCK-OUT TO BE CAPPED. CONNECT EMERGENCY LIGHT TO LINE SIDE OF CORRIDOR LIGHTING CIRCUIT, 2 #12 IN #5W WIREMOLD

2 #12 - 1½" C TO 30A-1P C/B IN COMPUTER LAB PANEL CP-1 CIRCUIT #2

RECONNECT TO EXISTING CIRCUIT. EXTEND CONDUIT AND WIRE AS REQUIRED

- EXISTING 2'-0" x 2'-0" RECESSED FLUORESCENT FIXTURES TO BE REMOVED

2 #12, 1/2" C. TO NEW 20A-1P C/B IN NEAREST 480/277 VOLT PANEL

CONNECT TO EXISTING EXIT LIGHTING CIRCUIT 2 # 12 1/2 EMT.

- EXISTING 8'-0" LONG 2-LAMP FLUORESCENT FIXTURES AND
- EXISTING 2'-0" x 2'-0" 4-LAMP FLUORESCENT FIXTURES TO BE REMOVED SEE GENERAL NOTES.

MATCH LINE SEE DWG. NO. E05-2

3 #8 + 1 #8 GND, 1" C. RUN ABOVE CEILING

PULL BOX SIZE AS REQUIRED

DEMOLITION PART PLAN

1/8" = 1'-0"

CLOCK/SPEAKER RISER DIAGRAM

N.T.S.



JANSEN & ROGAN
CONSULTING ENGINEERS, P.C.
121 WHITNEY AVENUE
NEW HAVEN, CT. 06510

STATE OF CONNECTICUT
WILLIAM J. JANSEN
No. 7590
PROFESSIONAL ENGINEER

STATE PROJECT # 034-89-105-EA

Antinozzi Associates Architects
4021 Main Street
Stratford, Connecticut

DANBURY SCHOOL REORGANIZATION
CITY OF DANBURY

MILL RIDGE INTERMEDIATE

DANBURY CONNECTICUT

UNIT 'B & C'
FLOOR PLAN, DEMOLITION, CLOCK AND SPEAKER RISER & HAND WASH SINK ELECTRICAL & PLUMBING

E05-1

CHECKED BY | SCALE 1/8" = 1'-0" | DATE : MAY 8, 1991 | JOB NO.